

Portable Gas Monitor GW-3

Operation Manual (PT0-188)

RIKEN KEIKI Co., Ltd.

2-7-6 Azusawa, Itabashi-ku, Tokyo, 174-8744, Japan Website: http://www.rikenkeiki.co.jp/

Contents

1.	Product Overview	4
	1-1. Introduction	
	1-2. Intended use	
	1-3. DANGER, WARNING, CAUTION, and NOTE	
2.	Important Safety Information	
	2-1. Danger information	8
	2-2. Warning information	10
	2-3. Caution information	13
	2-4. Safety information	17
3.	Product Configuration	20
	3-1. Main unit and accessories	20
	3-2. Part names and functions	22
	3-2-1. Main unit	22
	3-2-2. LCD display	23
	3-3. Inserting the battery	25
4.	Alarm Functions	28
	4-1. Gas alarm types and alarm setpoints	28
	4-2. Gas alarm activation	31
	4-3. Fault alarm activation	33
	4-4. Outside operating temperature range warning	34
5.	Usage Instrucions	35
	5-1. Usage note	35
	5-2. Preparing startup	35
	5-3. Turning on the power	36
	5-4. Performing air calibration	42
	5-5. Measuring gas concentration	45

5-6. Checkin	g the gas concentration, alarm setpoints, etc. (display mode)	47
	rocedure for displaying display mode	
5-6-2. Ite	ems displayed in display mode	48
5-7. Turning	off the powerettings	53
6. User Mode S	ettings	54
6-1. User mo	de settina procedure	54
6-2. User mo	de setting items	57
7. Maintenance	de setting items	61
7-1. Mainten	ance intervals and maintenance items	61
8. Storage and	Disposal	63
	res for storage or when not in use for extended periods	
8-2. Product	disposal	64
9. Troubleshoot	ing	65
	abnormalities	
10. Product Spec	sifications	67
	on specifications	
	cations by model	

1

Product Overview

1-1. Introduction

Thank you for your purchase of the GW-3 Portable Gas Monitor ("product" hereinafter).

This operating manual describes product operating procedures and specifications. It provides information essential to correct use of the product. Make sure you have read and fully understood the contents of this manual before using the product. Keep this operating manual on hand to allow ready reference during use.

For more information on product maintenance and configuration changes, refer to the technical manual that can be downloaded from Website.

The contents of this manual are subject to change without notice to allow product improvements. Any duplication or reproduction of this manual without permission is prohibited, whether in whole or in part.

Riken Keiki accepts no liability for accidents or damage resulting from use of the product, whether within or outside the warranty period.

Review the warranty policy indicated on the warranty.

<Checks made after purchase>

Before using the product, please confirm that the model of the product you purchased matches the model of the product covered by this operating manual.

Models covered by this operating manual

- GW-3 (O2)
- GW-3 (OX)
- GW-3 (CO)
- GW-3 (HS)
- GW-3 (C-)
- GW-3 (CX)

<This operating manual>

In this operating manual, where descriptions differ according to the model, the following icons are used to indicate each of the models:

GW-3 (O2)	O2
GW-3 (OX)	OX
GW-3 (CO)	CO
GW-3 (HS)	HS
GW-3 (C-)	C-
GW-3 (CX)	CX

Operating procedures and specifications for which no icons appear apply to all models.

In cases without significant differences from model to model, the display examples are taken from the GW-3 (CO) (detection target gas: CO (carbon monoxide)).

1-2. Intended use

The product is a portable gas monitor for personal use designed to detect gases in the surrounding atmosphere. It measures concentrations of toxic gases and oxygen in the atmosphere and issues an alarm when gas concentrations reach preset levels, thereby alerting users to the hazards of gas poisoning and oxygen deficiency. The detection results are not intended to assure life or safety.

Six models are available to detect various detection target gases.

Check the specifications before use to confirm the correct gases will be detected in accordance with the intended purpose.

<List of detection target gases by model>

Model	Detection target gas	
GW-3 (O2)	Oxygen(Galvanic cell type)	
GW-3 (OX)	Oxygen(Electrochemical type)	
GW-3 (CO)	Carbon monoxide	
GW-3 (HS)	Hydrogen sulfide	
GW-3 (C-)	Carbon monoxide*	
GW-3 (CX)	Carbon monoxide, oxygen	

^{*}The carbon monoxide sensor (ESR-A1CP) includes a correction function to reduce hydrogen interference. This function works for hydrogen concentrations up to 2,000 ppm.

1-3. DANGER, WARNING, CAUTION, and NOTE

This operating manual uses the following categories to indicate potential damage/hazards if the user disregards the information provided and uses the product incorrectly:

DANGER	This indicates situations in which improper handling may result in fatal or serious injury or significant property damage.
WARNING	This indicates situations in which improper handling may result in serious injury or significant property damage.
CAUTION	This indicates situations in which improper handling may result in minor injury or minor property damage.

Additionally, usage recommendations are indicated as follows:

NOTE	This indicates items that will be helpful to know when using the product.
------	---

2

Important Safety Information

To maintain the performance of the product and to ensure safe use, always observe the following DANGER, WARNING, and CAUTION instructions.

2-1. Danger information



Explosion-proofing

- Do not modify or alter the circuitry or configuration.
- When using the product in hazardous areas, take the following precautions to safeguard against static electricity hazards:
 - Wear anti-static clothing and conductive shoes (anti-static work shoes).
 - When using the product indoors, stand on a conductive work floor (with a leakage resistance of 10 M Ω or less).
- Be sure to replace the battery in a safe place.
- The explosion-proof class of the product is Ex ia IIC T4 Ga.
- The ratings are as follows:
 - Japan models:

Power supply: 3 V DC, 1 mA (using one Murata CR2450 battery)

Ambient temperature: -20 °C to +60 °C

Export models:

Power supply: 3 V DC, 1 mA (using one Murata CR2450, Sony CR2450B, or Duracell DL2450

battery)

Ambient temperature: -20 °C to +60 °C

• If the product is used as an explosion-proof device, note that the explosion-proofing rating conditions specify the battery type to be used.

The battery types are as follows:

Japan models: One CR2450 (Murata)

Export models: One CR2450 (Murata), CR2450B (Sony), or DL2450 (Duracell)





Usage

• When measuring inside manholes or enclosed spaces, never lean over or look into the manhole or enclosed space.

Such locations may generate and discharge oxygen-deficient air or other gases.

2-2. Warning information



WARNING

Fresh air adjustment in the atmosphere

When air calibration is performed in the atmosphere, check the atmosphere for freshness before starting.
 The presence of interference gases will prevent proper air calibration. The presence of interference gases is also extremely dangerous because the product may not detect actual gas leaks correctly.

Battery level check

 Check battery levels before using the product. The battery may become depleted if not used for extended periods.

Always replace with a new battery before use.

The battery types are as follows:

- Japan models: One CR2450 (Murata)
- Export models: One CR2450 (Murata), CR2450B (Sony), or DL2450 (Duracell)
- If a low battery voltage alarm occurs, gas cannot be detected. If a low battery voltage alarm occurs during
 use, turn off the power and replace the battery.

Handling the calibration gas

- The calibration gas is nitrogen or toxic gas. Inhaling the gas may lead to loss of health or even death.
 When using calibration gas, discharge outside, perform calibration in a well-ventilated area, or use local ventilation equipment.
- Calibration gas must be used by itself. Calibration can be performed with a gas mixture. However, calibrations performed with a gas mixture will result in poor sensitivity and inaccurate concentration readings. But, in the calibration of GW-3(CX), nitrogen and carbon monoxide can use not only itself but also the mixed gases.

Sensor handling

- Never disassemble the electrochemical type sensor inside the product.
 Contact with the electrolyte inside the sensor may result in skin inflammation. Contact with eyes may result in blindness. Contact with clothing may result in discoloration or holes. If contact with electrolyte occurs, rinse the area immediately with plenty of water.
- Do not use any gas other than nitrogen as the balance gas when calibrating or adjusting an oxygen sensor.

Miscellaneous

- Do not dispose of the product into fire.
- Do not wash the product, either in a washing machine or an ultrasonic cleaning machine.
- Do not block the buzzer sound opening. Doing so will muffle or silence the audible warning.
- Do not remove the battery while the power is turned on.



WARNING





Battery replacement or sensor replacement

- An OVER alarm may occur if the power is turned on within 10 minutes of replacing the battery or the sensor.
 This is due to the characteristics of the sensor.
 - If an OVER alarm occurs in fresh air after replacing the battery or the sensor, turn off the power, then turn the power on again after waiting at least 10 minutes.



Handling the calibration gas

- The carbon monoxide sensor with hydrogen compensation must be calibrated separately for carbon monoxide and hydrogen.
- If hydrogen sensitivity calibration is not performed, carbon monoxide readings may be inaccurate due to hydrogen interference.
- Due to the hydrogen compensation mechanism, carbon monoxide readings may increase temporarily if hydrogen gas concentrations increase rapidly in the atmosphere being measured.

2-3. Caution information



Do not use the product in locations where it may be exposed to oil, chemicals, or other such substances. Avoid deliberately submerging the product in water.

- Do not use the product in locations where it may be exposed to oil, chemicals, liquids, or other such substances. **Do not use walkie-talkies near the product.**
- The product's functions may be affected by radio waves emitted from walkie-talkies or other radio transmitters used nearby.
 - Position any transceivers or other similar devices so that they do not affect the product's functions.
- Avoid using the product near devices that emit strong electromagnetic radiation (high frequency or high voltage devices).

Be sure to perform regular maintenance.

The product is a safety device. Maintain the product regularly to ensure safety.
 Continuing to use the product without adequate maintenance will result in sensor sensitivity variations, preventing accurate gas detection.

Maintenance

- Replace filters every six months.
- Handle filters carefully. Do not use damaged filters.

Do not use the product in locations outside the operating temperature and humidity ranges.

• The operating temperature and humidity ranges for the product are as follows: Avoid using the product at temperatures or humidity levels outside the indicated operating range.

GW-3(O2):

Continuous use environment: Temperature: −20 °C to +50 °C Humidity: 10 %RH to 90 %RH

<u>GW-3(OX),GW-3(HS),GW-3(CO),GW-3(C-),GW-3(CX)</u>:

Continuous use environment: Temperature: -20 °C to +50 °C Humidity: 10 %RH to 90 %RH Temporary use environment: Temperature: -20 °C to +60 °C Humidity: 0 %RH to 95 %RH

• Avoid using for extended periods in locations exposed to direct sunlight.

- Avoid storing the product inside parked vehicles in hot weather.
- Note that humidity may affect readings even when humidity is within the specified range.

Air calibration

- Air calibrate the product using fresh air at pressures, temperatures, and humidity levels similar to the actual usage environment.
- Wait for the readout to stabilize before performing air calibration.
- If the temperature difference between the storage location and usage location is 15 °C or greater, turn on the power, allow the product to adjust to ambient conditions similar to those at the usage location for about a few tens of minutes*1, and perform air calibration using fresh air before using the product.

Miscellaneous

- Pressing buttons unnecessarily may change settings and prevent alarms from activating correctly. Avoid performing any operations not described in this operating manual.
- Do not drop the product or subject it to impact. Doing so may degrade waterproof and explosion-proof performance or reduce sensitivity.
- Do not poke the sensor or buzzer sound opening with sharp or pointed items. Doing so may result in malfunctions or damage to the product, preventing accurate measurements.
- The product is a precision device. Do not subject the product to strong impact or vibration.
- If the product is used in cold conditions, the intrinsic properties of the battery may cause the low battery voltage alarm to occur sooner than usual.
 - When using the product at temperatures below 0 °C, confirm that the battery level icon shows at least three bars.

- Keep the product away from magnetic fields. Magnetic fields may cause the product to fail or malfunction. If the product does not operate correctly, use it away from magnetic fields.
- Replace the battery promptly, then wait at least 10 minutes before turning the power on. If the product is stored for extended periods with the battery removed, a [FAIL SENSOR] (sensor abnormality) alarm may occur in rare cases when the power is turned on. If this occurs, wait at least a few tens of minutes*2 before turning the power back on.

Battery replacement

- Be sure to turn off the power for the product before replacing the battery.
- Always replace the battery with a new battery.
- Note the polarity when inserting a battery.
- Do not use any batteries other than the types specified.
- Be sure to replace the battery in a safe place.

Storage

• If the product will not be used for extended periods, store with the battery removed. Battery leaks may result in fire or injury.

*1 GW-3(O2):30 minutes / GW-3(OX),GW-3(HS),GW-3(CO),GW-3(C-),GW-3(CX):10 minutes

*2 GW-3(O2),GW-3(HS),GW-3(CO),GW-3(C-):5 minutes / GW-3(OX),GW-3(CX):10 minutes



CAUTION OX CO











Gas alarm activation

• If sensor has been exposed to high concentrations of gas (including the detection target gas or interference gas), it may take several minutes, or even several hours, for the display readout to return to zero (or 20.9 %). (For example, high concentrations of hydrogen, unsaturated hydrocarbons, alcohol, etc.)



CAUTION





Sensor

- Do not expose the product to sudden pressure fluctuations. Oxygen readings will fluctuate briefly, preventing accurate measurement.
- Do not use any gas other than nitrogen as the balance gas. Otherwise, oxygen reading errors will increase, preventing accurate measurement.



CAUTION



Calibration

- Calibration of hydrogen gas may become impossible when the product is used or stored for extended periods in dry environments.
 - If [FAIL A-CAL] (calibration abnormality) appears during hydrogen sensitivity calibration, leave the product

overnight or longer in a location with sufficient humidity, then perform calibration once again. If it is not possible to perform CO sensitivity calibration, contact Riken Keiki to request sensor replacement.

2-4. Safety information

This gas monitor is portable and is available as a single-gas monitor or a two-gas monitor.

A single CR2450 button-type lithium battery is used for power supply. Replace the battery in a safe place.

<Specification for safety>

- Ex ia IIC T4 Ga
- · (Ex) II 1G Ex ia IIC T4 Ga
- · Ambient temperature range: -20 °C to +60 °C

<Electrical data>

 Powered by one CR2450 lithium manganse dioxide battery (CR2450 by Murata, CR2450B by Sony, or DL2450 by Duracell)

(Only CR2450 by Murata can be used for Japan models.)

<Certificate numbers>

IECEx Certificate number: IECEx DEK 18.0082
 ATEX Certificate number: DEKRA 18 ATEX 0130

<List of standards>

- IEC 60079-0:2017
- IEC 60079-11:2011

- EN60079-0:2012+A11:2013
- EN60079-0:2018
- EN60079-11:2012

<Guidelines>

- JNIOSH-TR-46-1:2015
- · JNIOSH-TR-46-6:2015



WARNING

- Do not replace batteries in hazardous location.
- Do not disassemble or alter the product.
- Use only one CR2450 lithium manganse dioxide battery by Murata, CR2450B by Sony, or DL2450 by Duracell (CR2450 by Murata only for Japan models).

Note the following:

• Only CR2450 batteries can be used.

A: Manufacturing year (0-9)

B: Manufacturing month (1-9, XYZ for Oct.-Dec.)

RIKEN KEIKI

C: Manufacturing lot

D: Serial number

E: Code of factory

RIKEN KEIKI Co., Ltd.

2-7-6 Azusawa, Itabashi-ku, Tokyo, 174-8744, Japan

Phone: +81-3-3966-1113 Fax: +81-3-3558-9110 GIII Email: intdept@rikenkeiki.co.jp Website: http://www.rikenkeiki.co.jp


3

Product Configuration

3-1. Main unit and accessories

Open the box and packaging and inspect the main unit and accessories. If anything is missing, contact Riken Keiki.

<Main unit and standard accessories>



Standard accessories					
CR2450 battery: ×1 (fitted)	Spring bar: ×2 (fitted)				
		Product warranty: ×1	Operating manual: ×1		
Watch band: x1 Japan models (except for GW-3 (CX))	Belt clip: x1 Japan models (except for GW-3 (CX))	Alligator clip: x1 Export models	Heat-resistant case: x1 Japan models (GW-3 (CX) only)		

<Optional items (sold separately)>

- Dust filter
- Filters


GW-3 (CO), GW-3 (C-) : Filter CF-1821 GW-3 (CX) : Filter CF-6280

GW-3 (HS) : Humidity control filter CF-A13i-1

- Leather case
- Heat-resistant case
- Arm band (belt)
- Calibration adapter
- Data logger management program

3-2. Part names and functions

3-2-1. Main unit




No.	Name	Function		
1	Alarm lamp/ Infrared communication port	Flashes red when an alarm occurs. This is used for data communication with a PC when using the data logger management program (sold separately).		
2	Buzzer sound opening	Opening that emits operating and alarm sounds. Blocking the buzzer sound opening will muffle or silence the audible warning.		
3	LCD display	Displays the detection target gas name, gas concentration, battery level, etc.		
4	AIR button	Performs air calibration in measurement mode. Used to select functions when in user mode, etc.		

No.	Name	Function		
5	POWER/MODE button	Turns the power on/off. Confirms operations when in user mode, etc.		
6	Sensor	The sensor for detecting gas is installed.		
7	Battery cover	Cover protecting the battery		

^{*}The data logger management program is sold separately. For more information, refer to the operating manual for the data logger management program.

3-2-2. LCD display



No.	Name	Function	
1	Gas name/ concentration display	Displays the detection target gas name and gas concentration.	
2	Battery level icon	Indicates battery levels.	

No.	Name	Function		
3	Operating status display	Indicates the operating status in measurement mode. Blinks when normal. The blinking interval changes from approximately once every second to approximately once every two seconds if no operation is performed for about 30 seconds.		
4	Information display	Displays various information.		

- ▶ The following is a guide to battery levels:
 - : Sufficient / : Low / : Replace the battery.
 - The battery level icon will blink () if battery levels drop even further.
- ▶ If the bump test expiration setting is ON, [✓] will appear in the lower left of the LCD if the bump test expiration date has not passed. (Refer to the technical manual '6-4-2. Bump test expiration ON/OFF (BP.RMDR)'.)

3-3. Inserting the battery

When using the product for the first time or when battery levels are low, install a new (CR2450) battery.

1 Confirm that the power for the product is turned off.


If the power is on, hold down the POWER/MODE button for at least three seconds to turn off the power.

- 2 Use a Phillips-head screwdriver to loosen the battery cover retaining screw, then open the battery cover.
- 3 Remove the old battery, then insert a new battery noting the polarity.

Insert the battery by matching the polarity markings inside the product.

4 Close the battery cover, then tighten the battery cover retaining screw with the Phillips-head screwdriver.

Tighten the screws to a torque of 15 to 16 N·cm with the Phillips-head screwdriver.





• If the product is used as an explosion-proof device, note that the explosion-proofing rating conditions specify the battery type to be used.

The battery types are as follows:

Japan models: One CR2450 (Murata)

• Export models: One CR2450 (Murata), CR2450B (Sony), or DL2450 (Duracell)



WARNING OX





• An OVER alarm may occur if the power is turned on within 10 minutes of replacing the battery or the sensor. This is due to the characteristics of the sensor. If an OVER alarm occurs in fresh air after replacing the battery or the sensor, turn off the power, then turn the power on again after waiting at least 10 minutes.



- Be sure to turn off the power for the product before replacing the battery.
- When replacing the battery, always replace with a new battery.
- Note the polarity when inserting a battery.
- Do not use any batteries other than the types specified.
- Be sure to replace the battery in a safe place.
- The date and time setting screen will appear in the following cases. Set the date and time referring to the technical manual '6-12. Date and time setting (DATE)'.
 - When the battery is first inserted
 - When the battery is inserted after the product has been left for five minutes or longer without a battery when replacing the battery, etc.
 - When you have tried to turn the power on while the battery has been inserted with the wrong polarity
 - When a button is pressed without a battery when replacing the battery, etc.



• The sensor will take about five minutes to stabilize after the battery is replaced. After replacing the battery, wait at least five minutes before using the product.



• The sensor will take about 10 minutes to stabilize after the battery is replaced. After replacing the battery, wait at least 10 minutes before using the product.

4

Alarm Functions

4-1. Gas alarm types and alarm setpoints





A gas alarm is triggered if the concentration of the detected gas reaches or exceeds the alarm setpoints shown in the following table. (Self-latching)

Gas alarm types include the first alarm (WARNING), second alarm (ALARM), third alarm (ALARM H), and OVER alarm (OVER).

Alarm type		First alarm (WARNING)	Second alarm (ALARM)	Third alarm (ALARM H)	OVER alarm (OVER)
Target gas name	Oxygen	18.0 %	18.0 %	25.0 %	40.0 %

CO C-

A gas alarm is triggered if the concentration of the detected gas reaches or exceeds the alarm setpoints shown in the following table. (Japan models: Auto reset/Export models: Self-latching)

Gas alarm types include the first alarm (WARNING), second alarm (ALARM), third alarm (ALARM H), STEL alarm (STEL), integrated alarm (A-1H) or TWA alarm (TWA)*, and OVER alarm (OVER).

Alarm type		First alarm (WARNING)	Second alarm (ALARM)	Third alarm (ALARM H)	STEL alarm (STEL)	Integrated alarm (A-1H)	TWA alarm (TWA)	OVER alarm (OVER)	
Target	Carbon	Japan	50 ppm	150 ppm	150 ppm	200 ppm	150 ppm	-	2,000 ppm
gas name	monoxide	Export	25 ppm	50 ppm	1,200 ppm	200 ppm	-	25 ppm	2,000 ppm

^{*}Japan models: Integrated alarm/Export models: TWA alarm

HS

A gas alarm is triggered if the concentration of the detected gas reaches or exceeds the alarm setpoints shown in the following table. (Self-latching)

Gas alarm types include the first alarm (WARNING), second alarm (ALARM), third alarm (ALARM H), STEL alarm (STEL), TWA alarm (TWA), and OVER alarm (OVER).

Alarm type		First alarm (WARNING)	Second alarm (ALARM)	Third alarm (ALARM H)	STEL alarm (STEL)	TWA alarm (TWA)	OVER alarm (OVER)	
Target	Hydrogen	Japan	1.0 ppm	10.0 ppm	10.0 ppm	5.0 ppm	1.0 ppm	200.0 ppm
gas name	sulfide	Export	5.0 ppm	30.0 ppm	100.0 ppm	5.0 ppm	1.0 ppm	200.0 ppm



A gas alarm is triggered if the concentration of the detected gas reaches or exceeds the alarm setpoints shown in the following table. (Japan models: Auto reset/Export models: Self-latching)

Gas alarm types include the first alarm (WARNING), second alarm (ALARM), third alarm (ALARM H), STEL alarm (STEL), integrated alarm (A-1H) or TWA alarm (TWA)*, and OVER alarm (OVER).

Alarm type			First alarm (WARNING)	Second alarm (ALARM)	Third alarm (ALARM H)	STEL alarm (STEL)	Integrated alarm (A-1H)	TWA alarm (TWA)	OVER alarm (OVER)
	Carbon monoxide	Japan	50 ppm	150 ppm	150 ppm	200 ppm	150 ppm	-	2,000 ppm
Target gas name	Oxygen		18.0 %	18.0 %	25.0 %	-	-	-	40.0 %
	Carbon monoxide	Export	25 ppm	50 ppm	1,200 ppm	200 ppm	-	25 ppm	2,000 ppm
	Oxygen		18.0 %	18.0 %	25.0 %	-	-	-	40.0 %

^{*}Japan models: Integrated alarm/Export models: TWA alarm

- ▶ The default settings for gas alarm setpoints are as shown in the tables above.
- ▶ The setting values for the alarm setpoints can be changed. (Refer to the technical manual '6-5. Alarm setpoint setting (ALARM-P)'.)

4-2. Gas alarm activation


<Buzzer and alarm lamp patterns>

When a gas alarm occurs, the user will be alerted by the audible buzzer, flashing alarm lamp, and vibration. The behavior differs depending on the type of alarm.

Alarm type	First alarm (WARNING)	Second alarm (ALARM)	Third alarm (ALARM H)	STEL alarm (STEL)	Integrated alarm (A-1H)	TWA alarm (TWA)	OVER alarm (OVER)
Buzzer	alternating strong and weak beeps at about 1-second intervals: "Beep,	alternating strong and weak blips at	Repeated alternating strong and weak blips at about 0.5-second intervals: "Blip, blip, blip, blip"	Repeated alternating strong and weak beeps at about 1-second intervals: "Beep, beep"	Repeated alternating strong and weak blips at about 1-second and 0.5-second intervals: "Beep, beep"	alternating strong and weak beeps at about 1-second	Repeated alternating strong and weak blips at about 0.5-second intervals: "Blip, blip, blip, blip"
Alarm lamp	flashing at about	Repeated flashing at about 0.5-second intervals	Repeated flashing at about 0.5-second intervals	Repeated flashing at about 1-second intervals	Repeated alternating flashing at about 1-second and 0.5-second intervals		Repeated flashing at about 0.5-second intervals
Vibration			The product v	will vibrate when an	alarm occurs.		

<Gas alarm display>

When a gas alarm occurs, the alarm type is indicated on the LCD display and the corresponding gas concentration display blinks.



Display example: Carbon monoxide (CO) concentration: 200 ppm when the third alarm is triggered

NOTE

If the gas detection range is exceeded (over scale), [OVER] appears on the LCD display, and [∩∩∩∩] will blink in the gas concentration display area.



WARNING

 A gas alarm indicates the presence of extreme danger. The user must take appropriate action after taking appropriate steps to ensure safety.

- ▶ The alarm pattern can be checked in the alarm setpoint display in display mode. Note, however, that the gas concentration display will not blink in alarm tests. (Refer to the technical manual '7-4. Performing alarm tests'.)
- Press the POWER/MODE button to reset the gas alarm.

4-3. Fault alarm activation

A fault alarm is triggered if an abnormality is detected in the product.

Fault alarm types include system, battery voltage, clock, sensor, and calibration abnormalities.



If a fault alarm occurs, determine the cause and take appropriate action.
 If the problem lies with the product and the fault occurs repeatedly, contact Riken Keiki immediately.

In the event of a fault alarm, the user will be alerted by the audible buzzer and flashing alarm lamp.

Alarm type	Fault alarm	M OVER alarm (M OVER)		
Buzzer	Repeated intermittent beeps at about 1-second intervals: "Beep-beep, beep-beep"	Repeated intermittent beeps at about 1-second intervals: "Beep-beep, beep-beep"		
Alarm lamp	Repeated flashing at about 1-second intervals	Repeated flashing at about 1-second intervals		
LCD display	Display example: System abnormality	Display example: M OVER alarm		

- For more information on malfunctions (error messages), see '9. Troubleshooting'.
- ▶ The M OVER alarm (minus sensor failure) is an alarm triggered if the zero point falls below the minus side.
- Press the POWER/MODE button to reset the alarm.

4-4. Outside operating temperature range warning

If the product (other than the GW-3 (O2)) is used for 20 minutes or longer outside the operating temperature range, an outside operating temperature range warning (temperature range error) occures.

When a temperature range error occurs, either leave the product for five minutes or longer in the operating temperature range, or turn off the power of the main unit.

If an outside operating temperature range warning occurs, the user will be alerted by the audible buzzer and flashing alarm lamp.

Alarm type	Outside operating temperature range warning					
Buzzer	Repeated intermittent beeps at about 1-second intervals: "Beep"					
Alarm lamp	Repeated flashing at about 1-second intervals					
LCD display	Display example: Outside operating temperature range warning					

- Press the POWER/MODE button to reset the alarm.
- ▶ The outside operating temperature range warning does not apply to the GW-3 (O2).

5

Usage Instrucions

5-1. Usage note

Observe all usage precautions when using the product.

Failure to comply with these precautions may result in failure of the product or inability to perform normal gas measurement.

5-2. Preparing startup

Check the following before starting gas detection:

- Confirm that the protective film on the LCD display has been removed.
- · Confirm adequate battery levels.
- Confirm that the filters inside the product are neither contaminated nor clogged.



WARNING

 Protective film is attached to the LCD display of the product at the time of shipping to protect it against scratching.

Be sure to peel off this protective film before using the product. Explosion-proofing cannot be guaranteed if the protective film is left attached.

5-3. Turning on the power

power turns on.


Turn the power on and start the product.

When the power is turned on, various information, including date and time and alarm setpoints, will be displayed in sequence, followed by the measurement mode screen.

1 Hold down the POWER/MODE button (for at least three seconds).

The alarm lamp lights up, and the buzzer blips once.

When the power is turned on, the entire LCD display lights up. The display changes automatically, as shown below.






product switches to measurement

mode.

*Japan models: Calibration notification display/Export models: Calibration expiration display

once, and the power turns on.



Full scale First gas alarm setpoint Second gas alarm setpoint Setpoint

Integrated/TWA alarm setpoint*2



Measurement mode



The buzzer blips twice, and the product switches to measurement mode.

- *1 Japan models: Calibration notification display/Export models: Calibration expiration display
- *2 GW-3 (HS): TWA alarm setpoint GW-3 (CO), GW-3 (C-): Japan models: Integrated alarm setpoint/Export models: TWA alarm setpoint



Entire LCD display lights up.



The buzzer blips once, and the power turns on.

Calibration notification*1



Date and time




Battery level/ alarm pattern



Detection target gas name



Full scale



b-

First gas alarm setpoint



Second gas alarm setpoint



Third gas alarm setpoint



STEL alarm setpoint



Integrated alarm setpoint*2



Measurement mode




The buzzer blips twice, and the product switches to measurement mode.

^{*1} Japan models: Calibration notification display/Export models: Calibration expiration display


^{*2} Japan models: Integrated alarm setpoint/Export models: TWA alarm setpoint

<Basic operation flow>

After turning on the power, the product performs as follows when you press the AIR button or the POWER/MODE button.







5-4. Performing air calibration

Perform air calibration before measuring gas concentration.

Air calibration refers to zero adjustment required to ensure accurate measurement of gas concentrations.



WARNING

When air calibration is performed in the atmosphere, check the atmosphere for freshness before starting.
 The presence of interference gases will prevent proper air calibration. The presence of interference gases is also extremely dangerous because the product may not detect actual gas leaks correctly.



CAUTION













- Perform air calibration in an environment that meets all of the following conditions:
 - Pressures, temperatures, and humidity levels are similar to pressures, temperatures, and humidity levels in the actual usage environment.
 - In fresh air
- Wait for the readout to stabilize before performing air calibration.
- If the temperature difference between the storage location and usage location is 15 °C or greater, turn on the power and allow the product to adjust to ambient conditions similar to those at the usage location for about 10 minutes. After this, air calibrate in fresh air before use.




CAUTION 02

- Perform air calibration in an environment that meets all of the following conditions:
 - Pressures, temperatures, and humidity levels are similar to pressures, temperatures, and humidity levels in the actual usage environment.
 - In fresh air
- Wait for the readout to stabilize before performing air calibration.
- If the temperature difference between the storage location and usage location is 15 °C or greater, turn on the power and allow the product to adjust to ambient conditions similar to those at the usage location for about 30 minutes. After this, air calibrate in fresh air before use.
- 1 Hold down the AIR button in measurement mode.

The buzzer blips once, and air calibration starts.



2 Release the AIR button once the LCD display changes from [Air HOLD] to [AdJ RELEASE].



The display automatically returns to measurement mode once air calibration has been successfully completed.

- ▶ If air calibration fails, [FAIL AIR] will appear. Air calibration will not be performed.

 Press the POWER/MODE button to reset the fault alarm (calibration abnormality). Resetting the alarm displays the value before air calibration.
- ▶ If the quick calibration function is enabled, you can perform quick calibration after successful air calibration in measurement mode. To perform quick calibration, hold down the AIR button and release the AIR button when [E-CAL] appears. (Refer to the technical manual '6-11. Quick calibration time setting (E-CAL)'.)

5-5. Measuring gas concentration


The display automatically returns to measurement mode once air calibration has been successfully completed to measure the gas concentration.

The gas concentration will appear on the LCD display when measurement is complete.

If the gas concentration detected reaches the alarm setpoint at this time, a gas alarm is triggered. (Refer to '4-2. Gas alarm activation'.)



O2 (oxygen) gas concentration display



CO (carbon monoxide) gas concentration display



Upper row: CO
(carbon monoxide) gas
concentration display
Middle row: O2 (oxygen)
gas concentration display



WARNING

- A gas alarm indicates the presence of extreme danger. The user must take appropriate action after taking appropriate steps to ensure safety.
- Do not block the buzzer sound opening. Doing so will muffle or silence the audible warning.

- When the confirmation beep has been set, the buzzer sounds at the set interval during measurement. (Refer to the technical manual '6-7. Confirmation beep setting (BEEP)'.)
- ▶ The gas concentration alarm setpoints can be checked in display mode. (Refer to '5-6. Checking the gas concentration, alarm setpoints, etc. (display mode).)
- ▶ The LCD backlight lights up when you press the POWER/MODE button or the AIR button. The LCD backlight will go out after about 30 seconds if no operation is performed. Thirty seconds is the default setting. Change the default settings in user mode. (Refer to the technical manual '6-8. LCD lighting time setting (BL TIME)'.)
- ▶ The LCD backlight turns on automatically if an alarm is triggered.

5-6. Checking the gas concentration, alarm setpoints, etc. (display mode)


Check measurement results.

Switch to display mode to check items like maximum concentration of gas detected, alarm setpoints, date and time, and temperature. You can also adjust the buzzer volume.

5-6-1. Procedure for displaying display mode

1 Press the POWER/MODE button in measurement mode.

The buzzer blips once, and the product switches to display mode.



2 Press the POWER/MODE button to cycle through the items displayed.

Pressing the POWER/MODE button cycles through the displayed items.



Display example: With date and time display selected

Press the POWER/MODE button in the buzzer volume setting screen to end display mode and return to measurement mode.


- ▶ The product returns automatically to measurement mode if no button operations occur for about 20 seconds.
- When display mode item display setting (DISP.SET) is OFF, the buzzer volume setting is not displayed. To end display mode, press the POWER/MODE button in the alarm setpoint display screen. (Refer to the technical manual '6-10. Display mode item display ON/OFF (DISP.SET)'.)

5-6-2. Items displayed in display mode

Display item	LCD display			Display contents	
	O2 OX	CO HS C- Display example: GW-3(CO)	CX		
Detection target gas name display			02 [0	ppm ♥ %	Displays the name of the detection target gas. [CO] (carbon monoxide) is displayed in the upper row. [O2] (oxygen) is displayed in the middle row.

PEAK display (Lower limit value)	02 = 209;			Displays the minimum gas concentration detected since the power was turned on. You can clear the PEAK value (lower limit value) while the PEAK display (lower limit value) is on by holding down the AIR button until [RELEASE] appears.
PEAK display (Upper limit value)	02 ª 209; ₽ MA×	EO Opposition	209 x PERK	Displays the maximum gas concentration (or minimum oxygen concentration of GW-3(CX)) detected since the power was turned on. You can clear the PEAK value while the PEAK display is on by holding down the AIR button until [RELEASE] appears. Display example) GW-3(O2)
STEL display	_	ED PPM	D ₽	The time-weighted average for gas concentration over 15 minutes. The value is refreshed every 60 seconds.

Integrated display or TWA display		[[] 1] 1 3 1 1 3 1 1 3 1 1 1 1 1 1 1 1 1 1	₽ - 1H 60	Displays the integrated gas concentration value or TWA value*. The integrated value (A-1H) is the time-weighted average for gas concentration over one hour. The elapsed time from the start of measurement is displayed in minute increments to the right of [A-1H]. The TWA value (TWA) is the time-weighted average of the gas concentration over 8 hours per day or 40 hours per week. The value is refreshed every 60 seconds. *GW-3 (HS):TWA display *GW-3 (CO), GW-3 (C-), GW-3 (CX): Japan models:Integrated (A-1H) display/ Export models: TWA display
Date and time display	20 198	20 19 ⁸ ! !'	20 19 ^a 1 1 1	Displays the current time and date. Display example: January 1, 2019, 10:38
Temperatur e display	24[*	24[*	24[*	Displays the current temperature. The temperature indicated by the temperature display corresponds to the internal temperature of the product. This value differs from the actual ambient temperature. Display example: 24 degrees



				*GW-3 (HS):TWA display *GW-3 (CO), GW-3 (C-): Japan models: Integrated (A-1H) display/ Export models: TWA display
				[GW-3(CX)] Pressing the AIR button cycles through the settings in the following order: [F.S.] (FULL SCALE) \rightarrow [WARNING] \rightarrow [ALARM] \rightarrow [ALARM H] \rightarrow [STEL] \rightarrow [A-1H] or [TWA]*.
				*Japan models: Integrated (A-1H) display/ Export models: TWA display
Buzzer volume setting	H B	HI :	H 3	Displays the buzzer volume. Pressing the AIR button lets you change the buzzer volume. Pressing AIR button toggles the setting between [LO] (soft) and [HI] (loud).

▶ By pressing the AIR button and the POWER/MODE button at the same time while displaying any of the alarm setpoints in the alarm setpoint display of display mode, you can test the relevant alarm. (Refer to the technical manual '7-4. Performing alarm tests'.)

5-7. Turning off the power



- If the concentration display does not return to [0ppm] (or [20.9%] for oxygen) when you turn the power off, allow the product to stand in fresh air. Confirm that the display returns to [0ppm] (or [20.9%] for oxygen) before turning the power off.
- 1 Hold down the POWER/MODE button (for at least three seconds).

Hold down until the buzzer blips three times.

[OFF] appears on the LCD, and the power turns off.



6

User Mode Settings


6-1. User mode setting procedure

Set the date and time, alarm setpoints, and other settings in user mode.

<Displaying user mode setting screen>

Select the setting item in the user mode menu, then make the settings in the setting screen displayed.

- 1 Turn off the power.
 - Hold down the POWER/MODE button for at least three seconds to turn off the power.
- 2 Hold down the AIR button and the POWER/MODE button at the same time, then release them when the buzzer blips once. The entire LCD display lights up, and the user mode menu appears.



A password input screen will appear if the user mode password has been set.

Press the AIR button to enter the password, then press the POWER/MODE button to display the user mode menu.



3 Press the AIR button several times to select the setting item.

Pressing AIR button cycles through user mode menu screens.

For information on user mode setting items, see the technical manual '6-2. User mode setting items'.



Display example: With date and time setting (DATE) selected

4 Press the POWER/MODE button.

The setting screen will appear.

Make the settings in each of the setting screens.




- ➤ To display the user mode menu while configuring settings, hold down the AIR button and the POWER/MODE button at the same time.
- ▶ The user mode password is the four-digit number set in user mode password setting (PASS-W). For information on the user mode password, see '6-13. User mode password setting (PASS-W)'.

<Ending user mode>

1 When the settings are complete, press the AIR button several times to select [START], then press the POWER/MODE button.

User mode ends. The product will return to measurement mode after performing the same operation as when the power is turned on.





WARNING

• Be sure to return to measurement mode after user mode settings are complete. The product will not return automatically to measurement mode if left in user mode.

6-2. User mode setting items

The following items can be set in user mode:

Item	LCD display	Details
Bump test (BUMP)	a ■ ■	Perform a bump test (function check). The bump test is a test for checking whether the readings are within the acceptable range by introducing a calibration gas. For information on the bump test procedure, see the technical manual '7-3. Performing bump tests'.
Calibration (GAS CAL)	B ▼ GAS CAL	Perform air calibration and AUTO calibration. For information on the calibration procedure, see the technical manual '7-2. Performing calibration'.
Calibration expiration setting (CAL SET)	ERL SET	Toggle the calibration expiration for AUTO calibration ON/OFF, set the number of days for calibration expiration, and set the operation after calibration date expires. *Settings available on export models only
Bump test expiration setting (BUMP.SET)	aumpset	Set the various conditions for bump testing, toggle the bump test expiration ON/OFF, set the bump test expiration date interval, and set the behavior after bump test expiration.

Alarm setpoint setting (ALARM-P)		Set alarm setpoints ^{*1} . You can also return the alarm setpoints to their default settings.		
	■ ▼ <i>ALARMP</i>	• GW-3 (CO), GW-3 (C	DX): First to third alarm setpoints	
Lunch break ON/OFF (LUNCH)		Set the lunch break setting to ON/OFF. The lunch break function retains the gas concentration values*1 from the last time the power was turned off and loads them to resume measurement the next time the power is turned on.		
	■ LUNCH		centration values are as follows: OX): PEAK value	
		, ,	ated value/Export models: TWA value	

Confirmation beep setting (BEEP)	1 ● 3 EE P	Toggle the confirmation beep ON/OFF, set its behavior, and set intervals. This function provides an audible indication of whether the product is operating normally. If the bump test expiration setting (BP.RMDR) or the calibration expiration setting (CAL.RMDR) is ON, you can have this function operate when the expiration date is reached.
LCD lighting time setting (BL TIME)	BL TIME	Set how long the LCD backlight remains on.
Key operation tone ON/OFF (KEY.TONE)	₽ KEY.TONE	Set the key operation tone ON/OFF.
Display mode item display ON/OFF (DISP.SET)	☐ ▼ DISPSET	Set the display ON/OFF for the items that can be set in display mode (buzzer volume setting).

Quick calibration time setting (E-CAL)	≘ •	Set the time for quick calibration. The quick calibration function performs AUTO calibration after the introduction of the calibration gas by automatically counting down the calibration time set with the quick calibration time setting (E-CAL).
Date and time setting (DATE)	IRTE	Set the date and time for the internal clock.
User mode User mode password setting (PASS-W)	₽ASSW	Set a password when transitioning to user mode. Set a password between 0000 and 9999.
ROM/SUM display (ROM/SUM)	₽ # # # # # # # # # # # # # # # # # # #	This displays the program number and SUM value of the product. This is normally not set or adjusted by the user.
Measurement start (START)	START	Return to measurement mode.

7

Maintenance

The product is an important safety and disaster-prevention device.

Perform product maintenance at regular intervals to ensure performance and to improve disaster-prevention and safety reliability.

7-1. Maintenance intervals and maintenance items

Maintain the following items at regular intervals:

Daily maintenance: Perform maintenance before commencing work.

• Monthly maintenance: Perform alarm tests monthly. (Refer to the technical manual '7-4. Performing alarm tests'.)

• Regular maintenance: Perform maintenance at least once a year (ideally, at least once every six months).

Maintenance item	Maintenance details	Daily maintenance	Monthly maintenance	Regular maintenance
Battery level	Check to confirm that battery levels are adequate.	0	0	0
Concentration display	Check to confirm that the concentration readout is [0ppm] ([20.9%] for oxygen) by measuring fresh air. If the readout is not [0ppm] ([20.9%] for oxygen), check to confirm that no interference gases are present, then perform air calibration.	0	0	0

Maintenance item	Maintenance details	Daily maintenance	Monthly maintenance	Regular maintenance
Main unit operation	Check to confirm that no fault alarm is displayed on the LCD display.	0	0	0
Filters	Check to confirm that the filters are not dirty.	0	0	0
Alarm test	Perform an alarm test. Check to confirm that the alarm lamp, buzzer, and vibration are functioning correctly.		0	0
Calibration	Calibration Perform calibration using a calibration gas.		_	0
Gas alarm check	Check the gas alarm using a calibration gas.	_	_	0



WARNING

• If you encounter a product abnormality, contact Riken Keiki immediately.

NOTE

- Calibration requires dedicated tools and the preparation of a calibration gas. Contact Riken Keiki before performing calibration.
- ▶ The built-in sensor has an expiration date and must be replaced regularly.
- ▶ The sensor needs to be replaced if you encounter symptoms like failure to restore readings after air calibration or fluctuating readings when performing calibration. Contact Riken Keiki for replacement.

3

Storage and Disposal

8-1. Procedures for storage or when not in use for extended periods

The product must be stored in the following environment:

- · In a dark place at normal temperatures and humidity and away from direct sunlight
- In a place free of gases, solvents, and vapor

Store the product in its shipping carton, if retained and available. If the shipping carton is not available, store away from dust and dirt.



 If the product is not to be used for extended periods, store with the battery removed. Battery leaks may result in fire or injury.

<Procedure for reuse>

Perform calibration if the product is used again after a period in storage. (Refer to the technical manual '7-2. Performing calibration'.)

8-2. Product disposal

Dispose of the product as industrial waste (incombustible) in accordance with local regulations.



WARNING

• Dispose of batteries in accordance with procedures specified by local authorities.

<Disposal in EU member states>

When disposing of the product in an EU member state, dispose of the battery separately.

The battery must be removed and disposed of appropriately in accordance with waste sorting and collection or recycling systems stipulated by the regulations of EU member states.

NOTE

Crossed-out recycle dustbin mark

The pictogram at right indicates that batteries must be separated from ordinary waste and disposed of appropriately.



This is affixed to products containing batteries to which EU Battery Directive 2006/66/EC applies. Such batteries must be disposed of appropriately.

9

Troubleshooting

9-1. Product abnormalities

Symptom	Cause	Corrective action
	The battery is depleted.	Turn off the power and replace with a new battery in a safe place. (Refer to '3-3. Inserting the battery'.)
The power cannot be turned	The battery was inserted with polarity reversed.	Reinsert the battery correctly. (Refer to '3-3. Inserting the battery'.)
on.	The POWER/MODE was pressed too briefly or for too long.	To turn the power on, hold down the POWER/MODE button for at least three seconds until the buzzer blips once. (Refer to '5-3. Turning on the power'.)
	The battery cover is not closed completely.	Close the battery cover completely.
System abnormality: [FAIL SYSTEM] appears.	A circuit abnormality occurred in the main unit.	Contact Riken Keiki for repair.
Sensor abnormality: The sensor sensitivity has degraded.		Contact Riken Keiki to request sensor replacement. (Refer to the technical manual '7-6-2. Sensor replacement'.)

Symptom	Cause	Corrective action		
Low battery voltage alarm: [FAIL BATTERY] appears.	Battery levels are low.	Turn off the power and replace with a new battery in a safe place. (Refer to '3-3. Inserting the battery'.)		
Air calibration is not	Fresh air is not being supplied to the product.	Supply fresh air around the product.		
possible. [FAIL AIR] appears.	The sensor sensitivity has degraded.	Contact Riken Keiki to request sensor replacement. (Refer to the technical manual '7-6-2. Sensor replacement'.)		
Clock abnormality: [FAIL CLOCK] appears.	Internal clock abnormality	Set the date and time. (Refer to the technical manual '6-12. Date and time setting (DATE)'.) If this occurs frequently, the internal clock may be faulty. Contact Riken Keiki to request internal clock replacement.		
The alarm does not stop even after gas concentrations fall below the alarm setpoint.	You did not press the POWER/MODE button.	For GW-3 (O2), GW-3 (OX), GW-3 (HS) The product alarms are self-latching. After the alarm occurs, press the POWER/MODE button. For GW-3 (CO), GW-3 (C-), GW-3 (CX) If the gas alarm pattern is self-latching, press the POWER/MODE button after the alarm occurs.		

▶ This troubleshooting section does not address all problems that may occur with the product. Brief explanations of causes and corrective actions have been provided to help correct common problems that may occur frequently. If problems persist even after taking the corrective actions suggested here or if you encounter symptoms not listed here, contact Riken Keiki.

10

Product Specifications

10-1. Common specifications

Concentration display	LCD digital display (segments + icons)					
Gas alarm indications	Flashing lamp, intermittent buzzer sounding, gas concentration display blinking, vibration					
Fault alarm/self diagnosis	Sensor abnormality, low battery voltage, faulty calibration, clock abnormality, system abnormality					
Fault alarm indications	Flashing lamp, intermittent buzzer sounding, fault information display					
Detection method	Diffusion type					
Power source	CR2450 button-type lithium battery					
Protection level	IP66/68 (2 m, 1 h) equivalent					
Explosion-proof construction	Intrinsically safe explosion-proof construction					
Explosion-proof class	Certificate of conformity for electrical equipment used in potentially explosive					
	atmospheres : Ex ia IIC T4 Ga					
	ATEX : II1G Ex ia IIC T4 Ga					
	IECEx : Ex ia IIC T4 Ga					
Certifications	Certificate of conformity for electrical equipment used in potentially explosive atmospheres, ATEX, IECEx					

External dimensions	Approx. 63 mm (W) × 42 mm (H) × 22 mm (D) (excluding projections)					
Weight	Approx. 45 g					
Function	Data logger, vibration, STEL, TWA, integrated value measurement (for CO models only, for Japan models only), quick calibration, peak value display, temperature display					

10-2. Specifications by model

Model	GW-3 (O	2)	GW-3	3 (OX)	G	6W-3 (HS)	G	W-3 (CO)	G	W-3 (C-)		GW-3	3 (CX)	
Detection target gas	Oxygen	ı	Оху	Oxygen		Hydrogen sulfide		Carbon monoxide		Carbon monoxide (reduced hydrogen interference)		Carbon monoxide		ygen
Detection principle	Galvanic cell	l type	Electrochemical type											
Display name	O2		C)2	H2S		СО		СО		CO		O2	
Sensor model	OS-BM2	С	ESR-	ESR-X13P2 ESR-A13i ESR-A13				SR-A13P	ES	ESR-A1CP ESR-X1DP				
Display range (1 digit)	0.0 to 40.0 %	o (0.1)	0.0 to 40.0 % (0.1)		0.0 to 30.0 ppm (0.1) 30.0 to 200.0 ppm (1.0)		0 to 300 ppm (1) 300 to 2,000 ppm (10)		0 to 300 ppm (1) 300 to 2,000 ppm (10)		0 to 300 ppm (1) 300 to 2,000 ppm (10)		0.0 to 40.0 % (0.1)	
Measurement range / Service range (Japan standard)		0.0 to 25.0 % / 0.0 to 25.0 % / 25.0 to 40.0 % 25.0 to 40.0 %		0.0 to 30.0 ppm / 30.0 to 200.0 ppm		0 to 500 ppm / 500 to 2,000 ppm		0 to 500 ppm / 500 to 2,000 ppm		0 to 500 ppm / 500 to 2,000 ppm		0.0 to 25.0 % / 25.0 to 40.0 %		
Measurement range / Service range (Export models)	0.0 to 25.0 % / 25.0 to 40.0 %		0.0 to 25.0 % / 25.0 to 40.0 %		0.0 to 100.0 ppm / 100.0 to 200.0 ppm		0 to 500 ppm / 500 to 2,000 ppm		0 to 500 ppm / 500 to 2,000 ppm		0 to 500 ppm / 500 to 2,000 ppm		0.0 to 25.0 % / 25.0 to 40.0 %	
Alarm setpoints (Japan standard)	LL 18. H 25.	.0 % .0 % .0 % .0 %	L LL H OVER	18.0 % 18.0 % 25.0 % 40.0 %	1st 2nd 3rd TWA STEL OVER	1.0 ppm 10.0 ppm 10.0 ppm 1.0 ppm 5.0 ppm 200.0 ppm	1st 2nd 3rd Integrate STEL OVER	50 ppm 150 ppm 150 ppm ted 150 ppm 200 ppm 2,000 ppm	1st 2nd 3rd Integrat STEL OVER	50 ppm 150 ppm 150 ppm ted 150 ppm 200 ppm 2,000 ppm	1st 2nd 3rd Integra STEL OVER	50 ppm 150 ppm 150 ppm ted 150 ppm 200 ppm 2,000 ppm	L LL H OVER	18.0 % 18.0 % 25.0 % 40.0 %

Alarm setpoints	L 18.0 % LL 18.0 %	L 18.0 % LL 18.0 %	1st 5 ppm 2nd 30.0 ppm 3rd 100.0 ppm	1st 25 ppm 2nd 50 ppm 3rd 1,200 ppm	2nd 50 ppm	1st 25 ppm 2nd 50 ppm 3rd 1,200 ppm	L 18.0 % LL 18.0 %
(Export models)	H 25.0 % OVER 40.0 %	H 25.0 % OVER 40.0 %	TWA 25 ppm STEL 5.0 ppm OVER 200.0 ppm	TWA 25 ppm STEL 200 ppm OVER 2,000 ppm	TWA 25 ppm STEL 200 ppm	TWA 25 ppm STEL 200 ppm OVER 2,000 ppm	H 25.0 % OVER 40.0 %
Alarm permitted setting range	L/LL 0.0 to 20.0 % H 21.8 to 40.0 %	L/LL 0.0 to 20.0 % H 21.8 to 40.0 %	1.0 to 200.0 ppm	20 to 2,000 ppm	20 to 2,000 ppm	20 to 2,000 ppm	L/LL 0.0 to 20.0 % H 21.8 to 40.0 %
Alarm delay time	Within 5 seconds	Within 12 seconds	Within 15 seconds	Within 30 seconds	Within 30 seconds	Within 30 seconds	Within 12 seconds
Gas alarm pattern	Self-latching	Self-latching	Self-latching	Japan models: Auto reset Export models: Self- latching	Japan models: Auto reset Export models: Self- latching	Japan models: Auto reset Export models: Self-latching	
Operating temperature range	-20 °C to +50 °C (no sudden changes)	In temporary ambient conditions for approx. 15 minutes: Continuous use environment: -20 °C to +60 °C (no sudden changes) -20 °C to +50 °C (no sudden changes)					
Operating humidity range	10 to 90 %RH (no condensation)	In temporary ambient conditions for approx. 15 minutes: 0 to 95 %RH (no condensation Continuous use environment: 10 to 90 %RH (no condensation to 90 %RH)					
Continuous operating time (25 °C, no alarm, no lighting)	Approx. 4,000 hours	Approx. 2,000 hours	Approx. 4,000 hours	Approx. 4,000 hours	Approx. 2,500 hours	Approx. 2,000 hours	
Response time (T90)	Within 20 seconds	Within 30 seconds					

Revision History

Issue	Revision details	Issue date
0	First issue	November 18, 2019
1	Addition \(\text{1-2. Intended use} \) / Correction \(\text{10-2. Specifications by model} \) / Addition \(\text{11-1. Data logger function} \) / Addition \(\text{CF-6280 filter for GW-3 (CX) accessories} \)	December 11, 2019
2	Change 「Text size」/ Renamed 「Operating Manual → Operation Manual」 * This Operation Manual corresponds to Technical Manual (PT0E-1930)	January 21, 2020

Declaration of Conformity

RIKEN KEIKI CO., LTD.

2-7-6, Azusawa, Itabashi-ku,

Tokyo 174-8744 Japan

declare in our sole responsibility that the following product conforms to all the relevant provisions.

Portable Gas Monitor GW-3 Product Name

Council Directives Model Name

2014/30/EU EMC

2014/34/EU **ATEX**

2011/65/EU RoHS EN 50270:2015(Type2) EN 61326-1:2013 EMC Applicable Standards

EN60079-0:2012+A11:2013 ATEX

IEC 61326-1:2012

EN60079-0:2018 EN60079-11:2012

EN50581(2012) RoHS **DEKRA Certification B.V** Name and address of the ATEX Notified Body

(NB 0344)

Meander 1051, 6825 MJ Arnhem P.O.Box 5185,6802 ED Arnhem

The Netherlands

DEKRA 18ATEX0130

1 March 2019 Number of the EU type examination certificate

DNV GL Presafe AS (NB 2460)

Name and address of the ATEX Auditing Organization

1363 Høvik Norway

Veritasveien 3

The Marking of the equipment or protective system shall include the following $\,:\,\,$ I 1G $\,$ Ex ia IIC T4 $\,$ Ga

Ex ia IIC T4 Ga

2019 Year to begin affixing CE Marking Signature: TOKYO, Japan Place:

Tetanya Kawa be Tetsuya Kawabe

Full name:

Director, Quality control center Title: 2019 Oct. 8, Date: